

AGATA VIDEO

Handset video intercom for
X1 and XIP systems

CAME  BPT



FEATURES

- Lock release button
- 3.5" LCD display
- Two keys for activating the auxiliary/porter call
- Self-inserting video of entry panels with cyclic selection
- Key for adjusting/excluding the ringtone (with alert LED when excluded)
- Colour saturation and screen brightness settings
- Up to 8 intercom calls
- "Panic" button for emergency call to the porter
- Program ringtones depending on the type of call
- Video bouncing function among indoor receiver during simultaneous calls
- Master/Slave function

AGATA VC/B 62100380

TECHNICAL SPECIFICATION

MODELS	AGATA VC/B
Dimensions (mm)	170 x 190 x 39
Power supply by BUS (V)	15 ÷ 20 DC
Absorption by BUS (mA)	175
Consumption in stand-by mode (mA)	<1
Operating temperature (°C)	+5 ÷ +40
Protection rating (IP)	30
Video standard	PAL/NTSC
Display	3.5" TFT LCD
Colour	White

ARTICLE / CODE DESCRIPTION

AGATA VC/B
62100380

Handset video intercom, 3.5" LCD display, 2 programmable AUX keys - white.
Building version with 8 Intercom calls.

Surface mounted monitor with 3.5" colour LCD display. The adjust/exclude ringtone keys, the colour and brightness saturation setting keys and the 2 auxiliary keys are on the left. The main keys are clearly visible and backlit, for door opening and self-insertion of video from the entry panel. It is equipped with a Master/Slave function and a video relaying between extensions function for simultaneous calls. Suitable for multi-user systems, with up to 8 intercom calls and with the "Panic" button for the emergency calls to the porter. It includes bracket for surface mounting on horizontal or vertical 503 box, 506E box and Ø 60 mm round box. Compatible with the X1 and XIP systems.

